

Claims

What is claimed is:

1 1. A finite impulse response filter cell, having at least three inputs and at
2 least two outputs, the finite impulse response filter cell coupled to receive a clocking
3 signal, comprising:

4 a multiplexer having at least two multiplexer inputs and an output, the
5 multiplexer operable at substantially half the clocking signal rate, each of the at least
6 two multiplexer inputs coupled to one of the at least three inputs of the finite impulse
7 response filter cell;

8 a multiplier including an output and at least two multiplier inputs, the first
9 multiplier input receiving a coefficient signal representing a FIR coefficient, the
10 second multiplier input coupled to one of the at least three inputs of the finite
11 impulse response filter cell;

12 a summer having at least two summer inputs and an output, the first and
13 second summer inputs coupled to receive the multiplexer output and the multiplier
14 output; and

15 at least two slave sample and hold circuits each having a slave input and a
16 slave output, the at least two slave inputs of the plurality coupled to the summer
17 output, the at least two slave outputs couple to form the at least two outputs of the
18 finite impulse response filter cell, each slave sample and hold circuit operable at
19 substantially half the clocking signal rate.

1 2. The finite impulse response filter of claim 1, wherein each coefficient
2 signal comprises a digital value.

1 3. The finite impulse response filter of claim 1 further comprises a
2 conversion circuitry coupled to the second multiplier input, the conversion circuitry
3 operable to convert a digital value at the second multiplier input into an analog
4 signal.

09851059-050301

1 4. A finite impulse response filter cell, having at least two inputs and an
2 output, the finite impulse response filter cell coupled to receive a clocking signal,
3 comprising:

4 a multiplier including an output and at least two multiplier inputs, the first
5 multiplier input receiving a coefficient signal representing a FIR coefficient, the
6 second multiplier input coupled to one of the at least two inputs of the finite impulse
7 response filter cell;

8 a summer having at least two summer inputs and an output, the first summer
9 input coupled to receive the multiplier output, the second summer input coupled to
10 one of the at least two inputs of the finite impulse response filter cell;

11 at least two slave sample and hold circuits each having a slave input and a
12 slave output, the at least two slave inputs coupled to the summer output, each slave
13 sample and hold circuit operable at half the clocking signal rate; and

14 a multiplexer having at least two multiplexer inputs and an output, each of the
15 at least two slave outputs coupled to one of the at least two multiplexer inputs, the
16 multiplexer operable at half the clocking signal rate, the multiplexer output couples
17 to form the output of the finite impulse response filter cell.

1 5. The finite impulse response filter of claim 4, wherein each coefficient
2 signal comprises a digital value.

1 6. The finite impulse response filter of claim 4, further comprises a
2 conversion circuitry coupled to the second multiplier input, the conversion circuitry
3 operable to convert a digital value at the second multiplier input into an analog
4 signal.

1 7. A finite impulse response filter having an input and an output,
2 comprising:

3 a master sample and hold circuit including a master input and a master
4 output, the master input coupled to form the input of the finite impulse response

09851059.05801
T08090"6505801

5 filter, the master sample and hold circuit operable to sample a first input signal and
6 hold the value of the first input signal on the master output for a first predetermined
7 period of time, the master sample and hold circuit operable at a clock speed;

8 at least two slave sample and hold circuits, each of the at least two
9 slave sample and hold circuits comprising a slave input and a slave output, each
10 the at least two slave inputs coupled to the master output, each of the at least two
11 sample and hold circuits operable to sample the master output signal and hold the
12 value of the signal on the plurality of slave outputs for a second predetermined
13 period of time, the at least two slave sample and hold circuits operable at
14 substantially $1/k$ times the clock speed of the master sample and hold circuit, where
15 k equals the number of slave sample and hold circuits;

16 a first multiplexer, having at least two first multiplexer inputs and a first
17 multiplexer output, each of the at least two first multiplexer inputs coupled to one of
18 the at least two slave outputs, the first multiplexer operable at substantially $1/k$ times
19 the clock speed of the master sample and hold circuit; and

20 at least one tap block having a tap block input and a tap block output,
21 the tap block input coupled to the first multiplexer output, the at least one tap block,
22 comprising,

23 a multiplier having a first and a second multiplier input and an
24 multiplier output, the first multiplier input coupled to the tap block input, the second
25 multiplier input coupled to receive a coefficient signal representing a FIR coefficient,

26 a summer including an output and a first and a second summer input,
27 the first input coupled to the multiplier output,

28 at least two slave sample and hold circuits, each of the at least two
29 slave sample and hold circuits comprising a slave input and a slave output, each
30 the at least two slave inputs coupled to the summer output, the at least two slave
31 sample and hold circuits operable at substantially $1/k$ times the clock speed of the
32 master sample and hold circuit, where k equals the number of slave sample and
33 hold circuits,

34 a second multiplexer, having at least two second multiplexer inputs
35 and a second multiplexer output, each of the at least two second multiplexer inputs
36 coupled to one of the at least two slave outputs of the tap block, the second
37 multiplexer operable at substantially $1/k$ times the clock speed of the master sample
38 and hold circuit, the second multiplexer output coupled to form the tap block output,
39 the tap block output couples to form a filter output.

1 8. The finite impulse response filter of claim 7, wherein each coefficient
2 signal comprises a digital value.

1 9. The finite impulse response filter of claim 7, further comprises a
2 conversion circuitry coupled to the second multiplier input, the conversion circuitry
3 operable to convert a digital value at the second multiplier input into an analog
4 signal.

1 10. An finite impulse response filter having an output, comprising:
2 a master sample and hold circuit including a master input and a master
3 output, the master input coupled to the input of the finite impulse response filter, the
4 master sample and hold circuit operable to sample a first input signal and hold the
5 value of the first input signal on the master output for a first predetermined period of
6 time, the master sample and hold circuit operable at a clock speed;

7 a plurality of slave sample and hold circuits, each of the plurality of
8 slave sample and hold circuits comprising a slave input and a slave output, each of
9 the plurality of sample and hold circuits operable to sample a signal and hold the
10 value of the signal on the plurality of slave outputs for a second predetermined
11 period of time, the plurality of slave sample and hold circuits operable at
12 substantially half the clock speed of the master sample and hold circuit;

13 a first pair of the plurality of slave sample and hold circuits having each
14 slave input directly connected to the master output;

09851059-050801

15 a plurality of multiplexers, each comprising at least a first and second
16 multiplexer input and an multiplexer output, the first multiplexer operable at
17 substantially half times the clock speed of the master sample and hold circuit, each
18 first and second multiplexer inputs coupled to one pair of slave outputs;

19 a plurality of multipliers, each of the plurality of multipliers including an
20 output and a first and a second multiplier input, each first multiplier input receiving a
21 coefficient signal representing a FIR coefficient, each second multiplier input
22 coupled to the output of the first multiplexer of the plurality of multiplexers; and

23 a plurality of summers, each of the summers including an output and a
24 first and a second summer input, each first summer input coupled to one of the
25 plurality of multiplier outputs, the second summer input of the first summer couples
26 to ground, each remaining second summer inputs coupled to one of the plurality of
27 multiplexer outputs, each pair of slave inputs succeeding the first pair of slave inputs
28 connected to one of the plurality of summer outputs;

29 the number of plurality of slave sample and hold circuits equals $2N$, the
30 number of plurality of multiplexers equals N , the number of plurality of summers
31 equals N , the number of plurality of multipliers $N+2$;

32 the multiplexer output of the last one of the plurality of multiplexers
33 couples to form the output of the finite impulse response filter.

1 11. The finite impulse response filter of claim 10, wherein each coefficient
2 signal comprises a digital value.

1 12. The finite impulse response filter of claim 10, further comprises a
2 conversion circuitry coupled to the second multiplier input, the conversion circuitry
3 operable to convert a digital value at the second multiplier input into an analog
4 signal.

1 13. A method of making an finite impulse response filter which has an
2 output, comprising the steps of:

3 coupling an input signal to a master input of a master sample and hold
4 circuit;
5 directly connecting a master output of the master sample and hold
6 circuit to a plurality of slave sample and hold circuits;
7 multiplexing the plurality of slave sample and hold circuit output
8 signals;
9 directly connecting the multiplexed output to at least one tap block cell
10 having a first and second input and an output, including a multiplier, a summer, a
11 plurality of slave sample and hold circuits and a multiplexer;
12 supplying a fixed tap coefficient signal to an input of the multiplier;
13 multiplying the first input of the tap block cell and the fixed tap
14 coefficient signal;
15 summing an output of the multiplier with the second input of the tap
16 block cell;
17 connecting an output of the summer to the inputs of the plurality of
18 slave sample and hold inputs of the tap block cell;
19 connecting the slave outputs of the plurality of slave sample and hold
20 circuits to the plurality of multiplexer inputs of the multiplexer in the tap block; and
21 multiplexing the slave output signals to generate the finite impulse
22 response filter output.

1 14. The method of claim 13, wherein the first input of the first tap block cell
2 is grounded.